

SPECIFICATION

Item No	LED36WUL (L120)
Input Voltage	AC110-240V 50/60Hz
Rated power	LED 36W
Safety Level	Class I
Extends height	1580mm
Closed height	1482mm
Extends Width	850mm
Extends depth	740mm
Lumens	3500Lm
Color Temperature	6400K
Light angle	360deg
LED lifetime	30000hrs
Ambient Temperature	-25°C ~ +60°C
Cable	H07RN-F 3x1.5mm ² x 3M Fitted with 110V 16A Plug
Net Weight	4.2kg
IP Rating	IP54
Maximum power outlet load	1500W
Socket for linking a maximum	Maximum link 15 lights

IP54



RoHS

CE



This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

AURORA LIGHT


Instruction Manual

IMPORTANT

It is essential that you read the instructions contained in this manual before using the light for the first time.

Failure to follow these instructions could result in damage to the light, property damage or personal injury.

This manual should be stored safely for future reference.



It's very important to read this manual carefully before you first use it.



IMPORTANT NOTE

Before using this AURORA LIGHT please read this manual and instructions for use carefully, if you do not understand any of the instructions please do not use this light and return it to your supplier. Please keep this manual for your reference.

PRODUCT INTRODUCTION

The 360° AURORA LIGHT is a portable 36 watt LED lighting unit designed for use on the worksite, in the workshop, garage or home, The AURORA LIGHT is supplied in 110v for temporary industrial application.

MAIN CONSTRUCTION

Transparent shade for Impact-resistant PC lens glare free, An alloy tripod, Long life SMD LED, Power cable and plug.

GENERAL SAFETY RULES

1. Always check that the voltage displayed on the nameplate is the same as the mains power source.
2. Never use an electrical appliance in the rain, in wet areas or with wet hands, using electrical appliance under these conditions greatly increases the possibility of electric shock.
3. Prior to operation, carefully inspect the light for any damage. Any part that is damaged, including the casing, cable or plug, should be properly and safely repaired or replaced by a qualified electrician before the light is used.
4. Please ensure that you read these instructions before using the AURORA LIGHT, and that all the safety guidelines are understood. Please keep these instructions for future reference.
5. Ensure the cable is positioned to avoid presenting a trip hazard.
6. Do not exceed the rated power loading for each type of lamp.

ACCESSORIES

- Threaded round hole strap retaining clip x1pc
- Adjustable nylon carrying strap x1pc
- Instruction manual x1pc

SETTING UP

The AURORA LIGHT is supplied with a removable adjustable carrying strap. Screw the strap retaining clip in to the threaded inset in the head of the lamp. The carry strap can then be clipped through the locating hole in the clip and then attached to the fixed clip on the base of the lamp.

The tripod stand fitted to the AURORA LIGHT is fully adjustable and allows the legs to be deployed to the required position and locked in place. To adjust the tripod slacken the thumbscrew on the sliding collar and then apply downward pressure to force the collar down opening the tripod legs. Maximum stability is achieved when the sliding collar is fully down and in contact with the base of the lamp. After use the tripod can be fully retracted by pulling the sliding collar upwards and locked in a closed position for easy transportation.

The AURORA LIGHT also features a power outlet that can be used to link several lamps together or as convenient power source for use with a power tool. Please note the total load applied should not exceed the following: Maximum power outlet load 1500w.

CLEANING

All exterior surfaces of the light can be wiped clean with a soft cloth dampened with a soap and water solution. Do not immerse or submerge any part of the light in water or any other solvent. Never use solvents or cleaning agents containing petroleum (petrol, kerosene, oil), paint thinner, turpentine, alcohol, or ammonia. Harsh materials like these can damage surfaces.

MAINTENANCE

In some States, Territories or Work Sites, Operator training or equipment documentation may be required. Please check with your Local Regulatory Authority prior to use.

All repairs should only be carried out by qualified service personnel. Do not open exterior casing of the light, as there are no user serviceable parts inside.

Opening or visible attempts to open or repair a light may void any guarantee and / or cause damage to the product or personal injury.