

ELITE 20W LED 110V TASK LIGHT

INSTRUCTIONS FOR USE



IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS AND CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. PLEASE KEEP INSTRUCTIONS SAFE FOR FUTURE USE.

SPECIFICATIONS

Item No	TLLLED20W
Lamp Type	100 LED SMD2835
Input Voltage	AC 110-130V 50/60Hz
Rated Power	20W
Safety Level	Class II
Lamp Lumens	2000Lm
Color Temperature	6400K
Lamp Light Angle	120°
LED Life Time	30000hrs
IP Rating	IP54
Lamp Head Size	273x243x136mm
Cable	H05VV-F 3x1.5mm ² x3M
Working Ambient Temperature	-25°C~60°C
Driver of LED	Constant-current sink LED driver
Material	Polycarbonate body, and opal glary free PC diffuser.



Plug & Socket


Fitted with 110V 16A plug BS EN60309
With 1 x 110V 16A Sockets BS EN60309
16 amp current (Max 1500W)

Socket for linking a maximum of 12 Elite 20 Watt Task Lights

Maximum total load applied to the Socket should not exceed 1500W

- ✓ 2011/65/EU RoHS Directive
- ✓ 2014/35/EU the LOW Voltage Directive
- ✓ 2014/30/EU the EMC Directive



 This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

INSTRUCTION

Do not use this task light in situations where flammable liquids, vapours or gases are present.
Do not allow this inspection lamp to get wet in storage or in use.
Do not use if the cable is damaged in any way.
The cable is not replaceable and if damaged this product must be discarded.
Avoid hanging the inspection lamp by the cable.

Please refer to the operating voltage, wattage and current rating of the product, which are stated on the rating label. The product must only be used on supplies and with equipment that are compatible with the rating label data. Disregard of this rating information could lead to serious injury and death. Note the IP rating of your product. Only use the product in accordance with the parameters of the IP rating. If in doubt, do not use the product in damp, wet or dusty atmospheres.

IMPORTANT

Safe disposal of waste electrical products, batteries and lamps. Where products are subject to the WEEE Directive and depict the crossed out wheeled bin on the packaging label and/or product label they MUST be disposed of in accordance with the WEEE directive. Note that waste electrical products, batteries and lamps should NOT be disposed of with household waste. Please recycle where appropriate facilities are available. Your Local Authority will be able to give recycling advice.

SAFETY WARNING

- This unit must only be connected to an appropriate power supply.
- When not in use always disconnect from the power supply.
- If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.
- Do not remove plug from mains supply by pulling on power cord.



THE HIRE SUPPLY COMPANY (UK) LTD
BUILDING NO. 2, SHEET STORES IND EST,
LONG EATON, NG10 1AU, UK